# **NI PXI-2557 Specifications**

# 2.5 GHz 75 $\Omega$ 8 x 1 Multiplexer (SP8T)

このドキュメントには、日本語ページも含まれています。

This document lists specifications for the NI PXI-2557 multiplexer module. All specifications are subject to change without notice. Visit ni.com/manuals for the most current specifications.

 $Topology......8\times 1\ multiplexer$ 

Refer to the *NI Switches Help* for detailed topology and front panel connector information.



**Caution** To ensure the specified EMC performance, operate this product only with shielded cables and accessories.



**Caution** Device relays might change state momentarily during electrostatic discharge.



**Caution** Refer to the *Read Me First: Safety and Electromagnetic Compatibility* document at ni.com/manuals for important safety and compliance information.

# **About These Specifications**

*Specifications* characterize the warranted performance of the instrument under the stated operating conditions.

Typical Specifications are specifications met by the majority of the instrument under the stated operating conditions and are tested at 23 °C. Typical specifications are not warranted.

# **Input Characteristics**

All input characteristics are DC, AC<sub>rms</sub>, or a combination unless otherwise specified.

Maximum switching voltage ....... 30 V

Maximum switching current .......... 0.5 A (per channel)

Maximum carry current......0.5 A (per channel)

Maximum RF power ......10 W



**Caution** The switching power is limited by the maximum switching current and the maximum voltage. Channel to common switching power must not exceed 10 W.



**Note** National Instruments recommends against switching active RF signals. As a relay actuates, the channel is momentarily unterminated. Some RF sources can be damaged by reflections if their outputs are not properly terminated. Refer to your RF source documentation for more information.

Typical DC path resistance

Path resistance is a combination of relay contact resistance and trace resistance. Contact resistance typically remains low for the life of a relay. At the end of relay life, the contact resistance rises rapidly above  $1.0~\Omega$ .

## **RF Performance Characteristics**

Characteristic impedance  $(Z_0)$ .........75  $\Omega$  nominal

Values in parentheses are typical.

Insertion loss

≤1 GHz	<1.1 dB (<0.6 dB)
≤2 GHz	<1.7 dB (<1.3 dB)
≤2.5 GHz	<2.15 dB (<1.75 dB)

Voltage standing wave ratio (VSWR)

≤1 GHz	<1.25 (<1.15)
≤2 GHz	<1.5 (<1.35)
≤2.5 GHz	<1.75 (<1.5)

Amplicon.com

IT and Instrumentation for industry

Sales: +44 (0) 1273 570 220 Website: www.amplicon.com Email: sales@amplicon.com



Typical isolation

≤1 GHz>48 dH	3
≤2 GHz>41 dH	3
<2.5 GHz>41 dF	3

Typical channel-to-channel skew .... <25 ps

Typical propagation delay ......1.2 ns

Typical rise time (10% to 90%) ......91 ps

Refer to Figures 1, 2, and 3 for typical insertion loss, typical VSWR, and typical isolation, respectively.




Figure 1. Typical Insertion Loss




Figure 2. Typical VSWR




Figure 3. Typical Isolation

## **Dynamic Characteristics**

Maximum relay operate time....... 10.4 ms



Note Certain applications may require additional time for proper settling. For information about including additional settling time, refer to the NI Switches Help.

Expected relay life

$Mechanical1 \times 10^6 \ cycles$
Electrical $3 \times 10^5$ cycles
(30 V. 10 mA, DC resistive)

## **Trigger Characteristics**

Input trigger

Sources ...... PXI trigger lines 0-7

Minimum pulse width......150 ns



Note The NI PXI-2557 can recognize trigger pulse widths less than 150 ns by disabling digital filtering. For information about disabling digital filtering, refer to the NI Switches Help.

Output trigger

Destinations ...... PXI trigger lines 0-7 Pulse width ...... Programmable (1 µs to 62 µs)

NI PXI-2557 Specifications

### **Physical Characteristics**

 $\begin{tabular}{ll} Relay type & & Electromechanical, \\ latching & & \\ I/O connectors & & 9 mini-75 Ohm SMB \\ jacks, gold plated & \\ PXI power requirement & & 3.7 W at 5 V, \\ 0.3 W at 3.3 V & \\ Dimensions (L \times W \times H) & & 3U, one slot, \\ PXI/cPCI module & 21.6 \times 2.0 \times 13.0 cm \\ (8.5 \times 0.8 \times 5.1 in.) & \\ Weight & & & 227 g (8.0 oz) & \\ \end{tabular}$ 

#### **Environment**

#### **Shock and Vibration**

Figure 4 shows the NI PXI-2557 power-on state.




Figure 4. NI PXI-2557 Power-On State

NI PXI-2557 Specifications



of MIL-PRF-28800F, Class 3.)

Figure 5 shows the NI PXI-2557 front panel connector.




Figure 5. NI PXI-2557 Front Panel Connector



**Note** For topology-specific connection information, refer to your device in the *NI Switches Help*.

#### **Accessories**

Visit ni.com for more information about the following accessories.

Table 1. NI Accessories for the NI PXI-2557

Accessory	Length	Part Number
Mini-75 Ohm SMB plug to mini-75 Ohm SMB plug coaxial cable	0.3 m	197211-0R3
	1.0 m	197211-01
Type F female to mini-75 Ohm SMB plug coaxial cable	0.3 m	197210-0R3

# **Compliance and Certifications**

#### Safety

This product meets the requirements of the following standards of safety for electrical equipment for measurement, control, and laboratory use:

- IEC 61010-1, EN 61010-1
- UL 61010-1, CSA 61010-1



**Note** For UL and other safety certifications, refer to the product label or the *Online Product Certification* section.

#### Electromagnetic Compatibility

This product meets the requirements of the following EMC standards for electrical equipment for measurement, control, and laboratory use:

- EN 61326-1 (IEC 61326-1): Class A emissions; Basic immunity
- EN 55011 (CISPR 11): Group 1, Class A emissions
- AS/NZS CISPR 11: Group 1, Class A emissions
- FCC 47 CFR Part 15B: Class A emissions
- · ICES-001: Class A emissions



**Note** For EMC declarations and certifications, refer to the *Online Product Certification* section.

## CE Compliance (

This product meets the essential requirements of applicable European Directives as follows:

- 2006/95/EC; Low-Voltage Directive (safety)
- 2004/108/EC; Electromagnetic Compatibility Directive (EMC)

NI PXI-2557 Specifications

4



#### Online Product Certification

To obtain product certifications and the Declaration of Conformity (DoC) for this product, visit ni.com/ certification, search by model number or product line, and click the appropriate link in the Certification column.

#### **Environmental Management**

NI is committed to designing and manufacturing products in an environmentally responsible manner. NI recognizes that eliminating certain hazardous substances from our products is beneficial to the environment and to NI customers.

For additional environmental information, refer to the NI and the Environment Web page at ni.com/environment. This page contains the environmental regulations and directives with which NI complies, as well as other environmental information not included in this document.

#### Waste Electrical and Electronic Equipment (WEEE)



**EU Customers** At the end of the product life cycle, all products must be sent to a WEEE recycling center. For more information about WEEE recycling centers, National Instruments WEEE initiatives, and compliance with WEEE Directive 2002/96/EC on Waste Electrical and Electronic Equipment, visit ni.com/environment/weee.

#### 电子信息产品污染控制管理办法 (中国 RoHS)



中国客户 National Instruments 符合中国电子信 息产品中限制使用某些有害物质指令 (RoHS)。关于 National Instruments 中国 RoHS 合规性信息, 请登录 ni.com/environment/rohs\_china。 (For information about China RoHS compliance, go to ni.com/environment/rohs\_china.)

**Amplicon**